







KitLock 1000 are a quick retrofit for keyed cam locks supplied as standard on a wide range of lockers, cabinets and cupboards. The keyless locks are easy to fit, taking just a few minutes to remove the existing cam lock and then making an additional top fixing for the new lock.

Technical Specifications

Power: 2 x 1.5 AAA Batteries Operations: 15,000 openings

When lock signals "Low Battery" there will be 100 Low Battery:

additional openings

Non-Volatile memory will be retained Memory:

when changing batteries

Battery Override: A 9volt battery can be placed against external

contacts

Material: Zinc Allov

1/16" (1.5mm) up to 1" (25mm) Door thickness:

KL1004 V up to 5mm (3/16") KL1005 V up to 16mm (5/8") KL1006 V up to 19mm (3/4") KL1007 V up to 25mm (1") 11 individual round buttons

Private or Public Functions:

IP55 rated with optional gasket

Fitting: Easy fit

Vertical, right and left hand models Fitting Options:

Finish: Silver grey and black (colour options available)

KitLock has 4 code levels; Codes:

> Master code, Sub-Master Code, User Code and Technician Code

Codes:

Buttons:

The lock is supplied with two factory preset codes.

11 33 55 77 Master Code: User Code: 22 44

Change both codes after lock has been installed.

All Master Codes 8 digits long All User Codes are 4 digits long

Functions:

Private Function:

This is the most common function and used where the same code will be repeatedly used, e.g a pupil in a school or an employee with the same locker in the workplace.

Public Function:

The KitLock operates with a single user code. The guest enters a personal four-digit code twice, the second time to confirm the correct code. This locks the lock. The same code is entered once only to open the lock before being erased and ready for the next user. This function is used for short term, multi occupancy applications, e.g a locker in a leisure centre.





